


Цвят:  светло сив**Electrical data****Ratings per IEC/EN**

Nominal voltage (III/3) 800 V

Rated current 32 A

Ex information

Rated current (Ex e II) 30 A

Physical data

Width 22,8 mm / 0.898 inch

Height 4,1 mm / 0.161 inch

Depth 19 mm / 0.748 inch

Jumper assignment 4-way

Material dataNote (material data) [Information on material data can be found here](#)

Color светло сив

Fire load 0.015 MJ

Weight 3.1 g

Commercial data

Product Group 22 (TOPJOB S)

eCl@ss 10.0 27-14-11-40

eCl@ss 9.0 27-14-11-40

ETIM 7.0 EC000489

ETIM 6.0 EC000489

PU (SPU) 25 Stück

Packaging type Bag

Country of origin VKOrg Germany DE

GTIN 4055143699846



Customs tariff number VKOrg Germany 85366990990

Изтегляния			
Documentation			
Additional Information		Bid Text	
Technical Section	pdf 2142.18 KB	2004-404	19.02.2019 xml 2.51 KB
		2004-404	28.04.2017 doc 23.50 KB

CAD/CAE-Data	
CAD data	CAE data
2D/3D Models 2004-404	EPLAN Data Portal 2004-404
	WSCAD Universe 2004-404
	ZUKEN Portal 2004-404

Бележки за инсталиране

Commoning



Insert push-in type jumper bar and push down until it hits backstop..


Removing a push-in type jumper bar:
Insert the operating tool between the jumper and partition wall of the dual jumper slots, then lift up the jumper.
Place the operating tool in the center of jumpers for up to five contacts (see above), or alternately on both sides for jumpers with more than five contacts.

Commoning	
Custom jumpers are created by breaking and removing jumper contacts (2000, 2001, 2002, 2004 Series).	Marking with a felt-tip pen.


Commoning




Stepping down via push-in type jumper bar.



Stepping down via push-in type jumper bar:
Commoning via closed terminal side with end plate allows jumpering over two cross-section sizes, e.g., from 16 mm² (6 AWG) to 6 mm² (10 AWG) or from 6 mm² (10 AWG) to 2.5 mm² (14 AWG) (see illustration above).



Stepping down via push-in type jumper bar:
Commoning via open terminal side with end plate allows jumpering over two cross-section sizes for 16 mm² (6 AWG) and 10 mm² (8 AWG) and one cross-section size for 6/4/2.5 mm² (10/12/14 AWG). An example: from 16 mm² (6 AWG) to 6 mm² (10 AWG) (see illustration above) or from 10 mm² (8 AWG) to 4 mm² (12 AWG).



Note:
The total current of the outgoing circuits must not exceed the nominal current of the step-down jumper/push-in type jumper bar.