



# Arké Metal: Axial 1P 10AX 2-way switch Metal

## 19104.M

Arké Metal / Devices / Basic devices

### Axial 1P 10AX 2-way switch Metal

Axial 1P 10 AX 250 V~ 2-way switch, lightable, replaceable button, Metal. Max 100 W for lamps with built-in power unit (IEC 60669-1:2017)

### Product Status

3 - Active

### Minimum order quantity

20 NR



## Technical data

- **Class group:** Domestic switching devices
- **Class:** Installation switch
- **Wiring system:** Two-way switch
- **Method of operation:** Rocker/button
- **Assembly arrangement:** Modular device for domestic switching devices
- **Number of modules (module system):** 1
- **Push button switch:** Yes
- **Number of rockers:** 0
- **Mounting method:** Flush mounted (plaster)
- **Type of fastening:** Engage (snap)
- **With mounting plate:** No
- **Material:** Plastic
- **Material quality:** Thermoplastic
- **Surface protection:** Lacquered
- **Surface finishing:** Matt
- **Colour:** Aluminium
- **RAL-number (similar):** 9007
- **Label space/information surface:** Yes
- **Illumination:** Optional
- **Function lighting:** Control and orientation
- **Suitable for degree of protection (IP):** IP40
- **Nominal voltage:** 250 v
- **Rated current:** 1.600 A
- **Feedback-signal contact:** No
- **Connection type:** Screwed terminal
- **Washing machine switch:** No

## Certifications

- 01. IMQ - Italy
- 10. EAC Eurasian Customs Union
- 15. CCC - China ([download](#))
- 28. NSW / RCM - Australia ([download](#))
- 29. QCERT - Colombia ([download](#))
- 36. ISI - India
- 37. Marking - Morocco
- 43. UKCA mark - Great Britain
- 92. RoHS UAE
- 96. Electrotechnical expert ([download](#))
- 99. WEEE Directive ([download](#))



## Packaging



8 0 0 7 3 5 2 6 8 4 7 0 6  
**Code** 8007352684706  
**Quantity** 1 NR  
**Dim.** 5.1x2.8x5.3 [cm]  
**Weight** 32.2 [g]



8 0 0 7 3 5 2 6 8 4 7 1 3  
**Code** 8007352684713  
**Quantity** 20 NR  
**Dim.** 27x11.6x6 [cm]  
**Weight** 709.4 [g]

## Legal

Vimar reserves the right to change at any time and without notice the characteristics of the products reported. Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed. For the terms of use of the information on the product info sheet see [Conditions of Use](#).