

BTICINO &gt; Door entry system &gt; 2 wires system &gt; LINEA 100 entrance panels



## 343100

Linea 100 two wires audio digital call pushbutton panel for wall mounted installation. The device consists in a pushbutton panel with 16 keys and a digital display for displaying the operating status. Through the recognition of previously saved numerical (SCS addresses) or alphanumerical codes (logic addresses), it can be used to call handsets, and to give residents the possibility of opening the door lock using a dedicated numerical code. The pushbutton panel can manage up to 4000 handset addresses (from 0 to 3999), and the direct call to the 2 WIRES switchboard. It has an internal contact (C – NO – NC) for the connection of an electrical door lock, or an external actuator (for the powering of the electrical door lock use an auxiliary transformer, item 336842). Connection (PL) for a local door lock release pushbutton. System power supply cuts do NOT cause the loss of memory data.

### Technical features

Protection index	IP44
Height	229 mm
Width	138 mm
Depth	42 mm
Numbers of calls	4000
Series	Linea 100

### Documentation

- [Technical data sheet](#)
- [Installer Manual](#)
- [Catalogue](#)